

English

Operating manual

PM / CO₂ Transmitter **PM[B]sense**



Members of GHM GROUP:

GREISINGER HONSBERG Martens /Seltaces VAL.CO

www.deltaohm.com

Keep for future reference.

TABLE OF CONTENTS

5
•

1 INTRODUCTION

PMsense is a **PM1.0**, **PM2.5** and **PM10** Particulate Matter transmitter suitable for outdoor air quality monitoring.

The dust particles concentration is measured using the laser scattering principle.

An optional CO₂ sensor can be integrated in the transmitter (**PMBsense**).

The transmitter has a digital RS485 output with MODBUS-RTU or ASCII proprietary protocol. A version with two additional 0/4...20 mA (0...10 V **on request when order-ing**) analog outputs is available. The two analog outputs can be independently associated with any of the measured parameters.

The measuring circuit of the transmitter can be operated in continuous mode or, in order to extend the PM sensor lifetime, at cyclic intervals (default operating mode). The measuring cycle interval is user configurable.

The transmitter is maintenance-free and has fast response, high sensitivity, excellent stability and long operating life.

	Measurement		Out	tput
Model	РМ	CO ₂	RS485	Analog ^(*)
PMsense-M	1		√	
PMsense-A	√		√	√
PMBsense-M	√	√	√	
PMBsense-A	\checkmark	√	√	√

Models

(*) Two analog outputs, standard 0/4...20 mA, on request 0...10 V.

2 TECHNICAL SPECIFICATIONS

Particulate Matter		
Measuring principle	Laser scattering	
Measured pollutants	PM1.0, PM2.5 and PM10	
Measuring range	01000 µg/m ³ (for each pollutant)	
Particle size detection range	Ø 0.310 μm	
Linearity error	< 5%	
Repeatability	< 3%	
Sensor warm up time	15 s	
Sensor lifetime	5 years approx. in 5 minutes cyclic operating mode (default) > 10,000 hours in continuous operating mode (1 meas./s)	
Temperature drift	< 0.01 µg/m³/°C	
CO ₂ (only PMBsense)		
Measuring principle	Double wavelength NDIR	
Measuring range	05000 ppm	
Accuracy	\pm (50 ppm+3% of measurement) @ 25 °C and 1013 hPa	
Response time	< 120 s (air speed= 2 m/s)	
Long-term stability	5% of measurement / 5 years	
Temperature drift	1 ppm/°C	
General specifications		
Output	RS485 with Modbus-RTU or ASCII proprietary protocol Only PMsense-A : 2 x analog 420 mA ($R_{Lmax} = 500 \Omega$); on request 2 x 010 V ($R_{Lmin} = 10 k\Omega$)	
Power supply	730 Vdc (1530 Vdc for 010 V analog outputs)	
Power consumption	25 mA @ 24 Vdc during measurement 4 mA in stand-by (only for cyclic operating mode) The indicated consumption does not include the consumption due to the analog outputs	
Connection	M12 8-pole circular connector	
Operating conditions	-20+70 °C / 095 %RH / 5001500 hPa	
Housing material	Polycarbonate	
Protection degree	Housing equipped with a rain-proof and UV resistant inlet air filter – IP 53	
Dimensions	120 x 94 x 71 (excluding M12 connector)	
Weight	330 g	

3 INSTALLATION

The transmitter is equipped with a bracket with U-bolt for the fixing to a Ø40...50 mm mast. It can be fixed to a wall using the bracket only, by removing the U-bolt.



Fig. 3.1: transmitter description

3.1 ELECTRICAL CONNECTIONS

The transmitter has a M12 8-pole circular connector and uses the **CPM12-8PM... op-tional** cables, with M12 8-pole connector on one side and open wires on the other side.



Connector pin N°	Function	CPM12-8PM wire color
1	Power supply negative (GND)	Blue
2	Power supply positive (+Vdc)	Red
3	Not used	
4	RS485 A/-	Brown
5	RS485 B/+	White
6	Digital and analog outputs ground (SGND)*	Grey
7	Analog output 1 positve (AOUT1, only PM[B]sense-A)	Yellow
8	Analog output 2 positve (AOUT2, only PM[B]sense-A)	Green
	Cable shield **	Black (thick wire)

 \ast The output ground (SGND) and the negative of the power supply (GND) are short-circuited inside the transmitter.

* The cable shield is not connected to the M12 connector.

To ensure a good noise immunity, it is recommended to connect the cable shield to ground (GND).

RS485 connection:

By default, the instrument has MODBUS address **1** and communication parameters 19200, 8E1. Different parameters can be set using the proprietary protocol or the MODBUS-RTU protocol.



Fig. 3.3: RS485 connection

Current analog output (only PM[B]sense-A):

By default, the current analog outputs are 4...20 mA, with:

4 mA = 0 μg/m³ 20 mA = 1000 μg/m³

The analog output 1 is associated by default to PM2.5. The analog output 2 is associated by default to PM10.

With the commands of the proprietary protocol it is possible to associate the analog outputs to different parameters, set the range 0...20 mA for the output and reverse the direction of the output, so that the output decreases as the measurement increases.

In case of measurement error, the output goes to 22 mA.



Power supply 12...30 Vdc

Fig. 3.4: current analog outputs connection

Voltage analog output (optional, only PM[B]sense-A):

By default, the voltage analog outputs are 0...10 V, with:

 $0 V = 0 \mu g/m^3$ 10 V = 1000 $\mu g/m^3$

The analog output 1 is associated by default to PM2.5. The analog output 2 is associated by default to PM10.

With the commands of the proprietary protocol it is possible to associate the analog outputs to different parameters, set the range 2...10 V for the output and reverse the direction of the output, so that the output decreases as the measurement increases.

In case of measurement error, the output goes to 11 V.



Fig. 3.5: voltage analog outputs connection

4 CONFIGURATION AND MEASUREMENT

The configuration of the instrument and the reading of the measurements can be done via the RS485 serial output, both with the proprietary protocol and with the MODBUS-RTU protocol.

In the first 10 seconds after the instrument power on, it is always active the proprietary protocol. After 10 seconds from power on, the operating protocol is activated, which by default is the MODBUS-RTU protocol.

It is possible to keep the proprietary protocol active even after 10 seconds from power on by sending, before the 10 seconds expire, the command **@** of the proprietary protocol. The proprietary protocol can be set as operating protocol by means of the DP0 command.

The commands of the proprietary protocol and the registers of the MODBUS-RTU protocol are described in detail in the following chapters.

Particulate Matter measurement modes:

The transmitter can perform the PM measurement in continuous mode or, in order to extend the sensor lifetime, at cyclic intervals (default).

In the measurement mode at cyclic intervals, the PM sensor is activated periodically for the ON time. The measurement is made available after 70 seconds from sensor activation (warm-up time). At the end of the ON time, the measurement is "frozen" and the sensor is deactivated until the set cyclic measurement interval expires.



Fig. 4.1: Measurement mode at cyclic intervals

The measurement mode, the cycle interval and the sensor ON time can be configured respectively by using the CPLS, CPLP and CPLO commands of the proprietary protocol or the holding registers with address 15, 16 and 18 of the MODBUS-RTU protocol.

The transmitter provides three types of measurements:

- average over a 10 seconds interval, updated every second;
- average over a 60 seconds interval, updated every 10 seconds;
- average over a 15 min interval, updated every minute.

For the measurement mode at cyclic intervals, the cycle interval and the ON time must be set consistently with the desired averaging interval.

Status of the transmitter:

There are two LEDs on the internal electronic board of the transmitter: the **green** LED indicates the presence of the external power supply (blinks once per second), the **red** LED indicates the presence of any measurement errors (normally off, it blinks twice per second if at least one of the measured parameters is in error).

5 PROPRIETARY PROTOCOL

To use the proprietary protocol, it is necessary to connect the instrument to the PC via a RS485/USB (e.g. RS51K) or RS485/RS232 converter and use a standard serial communication program. In the serial communication program, set the COM port number to which the instrument is connected and the communication parameters as follows:

- If the MODBUS-RTU protocol is set as the operating protocol in the instrument (default), set the Baud Rate 57600 and the parameters 8N2 in the serial communication program, then power cycle the instrument and send the command **@** within 10 seconds from the instrument power on.
- If the proprietary protocol is already set as the operating protocol in the instrument, it is possible to operate with Baud Rate 57600 and parameters 8N2 by sending the command @ within 10 seconds from the instrument power on, or you can let the 10 seconds pass without sending the command @ and operate with the communication parameters set in the instrument (default 19200, 8E1).

To change the instrument configuration, the serial command **CAL USER ON** must be sent first (the instrument replies with USER CAL MODE ON). The command CAL USER ON is automatically disabled after a few minutes of inactivity. If the settings should be only read, the command CAL USER ON is not required.

Below is the list of the serial commands.

Command	Reply	Description
G0	Model	Instrument model
G1	&Revision	Instrument hardware revision
G2	SN=nnnnnnn	Instrument serial number
G3	Firm.Ver.=x.y	Instrument firmware revision
G4	Firm.Date=yyyy/mm/dd	Date of firmware revision
GC	Fact.Calib.Date= yyyy/mm/dd User.Calib.Date= yyyy/mm/dd Cal.Mode= <i>Factory</i> or <i>User</i>	Date of factory calibration Date of user calibration (CO ₂ only) Type of calibration active (CO ₂ only)

Instrument information:

Protocol:

Command	Reply	Description
@	&	Keeps the proprietary protocol operational even after 10 seconds from instrument power on. It must be sent within 10 seconds from instrument power on.
DPn	&	Sets the operating protocol:
		 Proprietary if n=0 MODBUS-RTU if n=1
		Default : MODBUS-RTU (n=1)
GP	& n	Reads the operating protocol set in the instrument.
SM	&	Activates the MODBUS-RTU protocol immediately.
CMAn	&	Sets the instrument address for the MODBUS-RTU pro- tocol to n.
		The address should range within 1 and 247.
		Default : 1
RMA	& n	Reads the instrument address for the MODBUS-RTU pro- tocol.

Note: after sending the DP1 command, the instrument remains with the proprietary protocol. Send the command SM to activate the MODBUS-RTU protocol immediately, or power cycle the instrument.

Command	Reply	Description	
CMBn	&	Sets the Baud Rate:	
		 1200 if n=0 	■19200 if n=4
		• 2400 if n=1	■ 38400 if n=5
		4800 if n=2	▪ 57600 if n=6
		■ 9600 if n=3	■115200 if n=7
		<i>Default</i> : 19200 (n=4)	
RMB	& n	Reads Baud Rate setting	
CMPn	&	Sets parity and stop bits	:
		• 8N1 if n=0 [No parit	ty, 1 stop bit]
		 8N2 if n=1 [No parit 	ty, 2 stop bits]
		 8E1 if n=2 [Even pa 	rity, 1 stop bit]
		 8E2 if n=3 [Even pa 	rity, 2 stop bits]
		801 if n=4 [Odd particular sector is a sector if n=4 and not in the sector is a sector	rity, 1 stop bit]
		802 if n=5 [Odd particular sector is a sector of the sector is a sector of the sector is a sector is a sector of the sector is a sector of the sector is a sector of the sector of the sector is a sector of the	rity, 2 stop bits]
		The number of data bits	is fixed to 8.
		<i>Default</i> : 8E1 (n=2)	
RMP	& n	Reads the setting of pari	ty and stop bits.
CMWn	&	Sets waiting time after t protocol:	ransmission with MODBUS-RTU
		 Immediate reception Waiting 3.5 character 	n if n=0 (violates protocol) ers if n=1 (respects protocol)
		Default : Immediate rece	eption (n=0)
RMW	& n	Reads the setting of wait MODBUS-RTU protocol.	ting time after transmission with

RS485 communication parameters:

PM measurement settings:

Command	Reply	Description
CPLSn	&	Sets the PM measurement mode:
		 Continuous if n=0
		 At cyclic intervals if n=1
		<i>Default</i> : At cyclic intervals (n=1)
RPLS	& n	Reads the setting of the PM measurement mode.
CPLPn	&	Sets the cycle interval for the measurement mode at cy-
		clic intervals.
		<i>Default</i> : 300 (=5 min)
RPLP	& n	Reads the setting of the cycle interval for the measure-
		ment mode at cyclic intervals.
CPLOn	&	Sets the sensor ON time for the measurement mode at
		cyclic intervals to n seconds.
		It must be greater than 70 s (warm-up time).
		Default:71
RPLO	& n	Reads the setting of the sensor ON time for the measure- ment mode at cyclic intervals.

Reading of the measurement information:

Command	Reply	Description
CPSn	&	Sets the type of PM measurement averaging for the ana- log outputs and the measurements sent by the transmitter in reply to P1, P5, S1 and S5 commands or when reading MODBUS Input Registers 05:
		 Average over a 10 seconds interval, updated every second if n=0 Average over a 60 seconds interval, updated every 10 seconds if n=1 Average over a 15 minutes interval, updated every minute if n=2
		<pre>Default : Average over a 10 seconds interval, updated every second (n=0)</pre>
RPS	& n	Reads the type of averaging for the measurements sent by the transmitter in reply to P1, P5, S1 and S5 commands.
P0	&	Disable the sending of the measurement enabled with P1.
P1	&	Enable the sending of the PM measurement every second (the sequence is the same described in command P5).
P5	& Measurements	Prints the PM measurements in the following sequence:
		 PM measurement error (0=no, 1=yes)
		• PM1.0 in N° of particles/ml
		• PM2.5 in N° of particles/ml
		• PM10 in N° of particles/ml
		 PM1.0 in μg/m³
		■ PM2.5 in µg/m ³
		■ PM10 in µg/m ³
		<i>The PM measurement is averaged according to what is set with CPS command or MODBUS holding register 19.</i>
S0	&	Disable the sending of the measurement enabled with S1.
S1	&	Enable the sending of the measurement every second (the sequence is the same described in command S5).
S5	& Measurements	Prints the measurements in the following sequence:
		 PM measurement error (0=no, 1=yes)
		 PM1.0 in μg/m³
		 PM2.5 in μg/m³
		 PM10 in μg/m³
		■ CO2 in ppm
		 Atmospheric pressure in hPa (internal sensor for CO₂ measurement compensation)
		 Field not used
		 Field not used
		 Field not used
		 Power supply voltage
		 Internal board temperature
		<i>The PM measurement is averaged according to what is set with CPS command or MODBUS holding register 19.</i>

Analog outputs (only PM[B]sense-A):

Command	Reply	Description
CA1On	&	Enable/disable the offset of the analog output 1:
		 Offset disabled if n=0 (020 mA or 010 V) Offset enabled if n=1 (420 mA or 210 V)
		<i>Default</i> : Offset enabled $(n=1)$ if the output is current, offset disabled $(n=0)$ if the output is voltage (optional)
RA10	& n	Reads the setting of the offset for the analog output 1.
CA1SOn	&	Sets the direct or inverse correspondence between analog output 1 and associated physical quantity:
		• 4 mA/0 V \Rightarrow Min. quantity, 20 mA/10 V \Rightarrow Max. quantity if n=0
		• 20 mA/10 V \Rightarrow Min. quantity, 4 mA/0 V \Rightarrow Max. quantity if n=1
		<i>Default</i> : Direct correspondence (n=0)
RA1SO	& n	Reads the type of correspondence (direct or inverse) be- tween analog output 1 and associated physical quantity.
CA1Tn	&	Associates the analog output 1 to:
		 PM1.0 if n=0
		• PM2.5 if n=1
		 PM10 if n=2
		 CO₂ if n=12 (only PMBsense-A)
		Default : PM2.5 (n=1)
		<i>The PM measurement is averaged according to what is set with CPS command or MODBUS holding register 19.</i>
RA1T	& n	Reads the physical quantity associated to analog output 1.
CA1Ln	&	Sets n as the minimum value of the measuring range of the physical quantity associated to the analog output 1.
		If the output is associated to PM, the value must be expressed as a number of tenths (e.g. $n=5$ to indicate 0.5 μ g/m ³). If the output is associated to CO ₂ , the value must be expressed as a number of units (e.g. $n=200$ to indicate 200 ppm).
		Default: 0
RA1L	& n	Reads the minimum value of the measuring range of the physical quantity associated to the analog output 1.
CA1Hn	&	Sets n as the maximum value of the measuring range of the physical quantity associated to the analog output 1.
		If the output is associated to PM, the value must be expressed as a number of tenths (e.g. $n=50$ to indicate 5.0 μ g/m ³). If the output is associated to CO ₂ , the value must be expressed as a number of units (e.g. $n=800$ to indicate 800 ppm).
		<i>Default</i> : 10000 (=1000.0 μg/m ³ of PM)
RA1H	& n	Reads the maximum value of the measuring range of the physical quantity associated to the analog output 1.
RA1F	& Quantity Minimum value Maximum value	Simultaneously provides the information obtainable with the RA1T, RA1L e RA1H commands.

Command	Reply	Description
CA2On	&	Enable/disable the offset of the analog output 2:
		 Offset disabled if n=0 (020 mA or 010 V) Offset enabled if n=1 (420 mA or 210 V)
		Default : Offset enabled $(n=1)$ if the output is current,
		offset disabled (n=0) if the output is voltage (optional)
RA2O	& n	Reads the setting of the offset for the analog output 2.
CA2SOn	&	Sets the direct or inverse correspondence between analog
		output 2 and associated physical quantity:
		• 4 mA/0 V \Rightarrow Min. quantity, 20 mA/10 V \Rightarrow Max. quantity if n=0
		• 20 mA/10 V \Rightarrow Min. quantity, 4 mA/0 V \Rightarrow Max.
		quantity if $n=1$
		<i>Default</i> : Direct correspondence (n=0)
RA2SO	& n	Reads the type of correspondence (direct or inverse) be-
		tween analog output 2 and associated physical quantity.
CA2Tn	&	Associates the analog output 2 to:
		 PM1.0 if n=0
		• PM2.5 if n=1
		 PM10 if n=2
		 CO₂ if n=12 (only PMBsense-A)
		Default : PM10 (n=2)
		<i>The PM measurement is averaged according to what is set with CPS command or MODBUS holding register 19.</i>
RA2T	& n	Reads the physical quantity associated to analog output 2.
CA2Ln	&	Sets n as the minimum value of the measuring range of the physical quantity associated to the analog output 2.
		If the output is associated to PM, the value must be expressed as a number of tenths (e.g. $n=5$ to indicate 0.5 μ g/m ³). If the output is associated to CO ₂ , the value must be expressed as a number of units (e.g. $n=200$ to indicate 200 ppm).
		Default: 0
RA2L	& n	Reads the minimum value of the measuring range of the physical quantity associated to the analog output 2.
CA2Hn	&	Sets n as the maximum value of the measuring range of the physical quantity associated to the analog output 2.
		If the output is associated to PM, the value must be expressed as a number of tenths (e.g. $n=50$ to indicate 5.0 μ g/m ³). If the output is associated to CO ₂ , the value must be expressed as a number of units (e.g. $n=800$ to indicate 800 ppm).
RA2H	& nl	Reads the maximum value of the measuring range of the
		physical quantity associated to the analog output 2.
RA2F	& Quantity Minimum value Maximum value	Simultaneously provides the information obtainable with the RA2T, RA2L e RA2H commands.

CO₂ calibration (only PMBsense...):

A 2-point (CO21 and CO22 commands) or 1-point calibration (CO20 command) can be performed. The points are chosen by the user. To perform the calibration, the transmitter must be placed in an environment with a known CO_2 concentration.

While the 2-point calibration allows moving the two calibration points independently, and therefore also to adjust the slope of the sensor response curve, the 1-point calibration simply adds an offset to the measurement (the two calibration points are shifted of the same amount) and is typically accomplished by placing the transmitter in clean air.

Before performing the calibration, the type of calibration to be used must be set to "user" with the CC command.

The transmitter allows manually setting, with the DA command, a string that is saved as the date and time of the calibration. The string must be set before performing the calibration.

Command	Reply	Description
CO21n	& t	CO_2 calibration in the first point at n ppm.
		The transmitter must first be placed in an environment with a known CO_2 concentration (the value n entered in the command).
		The value t in the reply to the command indicates the number of seconds required for the transmitter to com- plete the calibration operation. During this time, the transmitter sends strings notifying the progress of the operation; for example:
		"CO2 calib. Status:IN PROGRESS 8% Avg:1096ppm Dev:0ppm"
		At the end, the OK 100% notification indicates that the operation was successful; for example:
		"CO2 calib. Status:OK 100% Avg:1100ppm Dev:7ppm"
CO22n	& t	CO ₂ calibration in the second point at n ppm.
		Operation similar to the CO21command.
CO2On	& t	CO ₂ calibration at n ppm (1-point calibration – offset ad- justment).
		Operation similar to the CO21command.
DAyyyy/mm/dd hh:mm:ss	&	Saves the string "aaaa/mm/gg hh:mm:ss" as the date and time when calibration is performed.
		The command must be sent before performing the cali- bration.
GA	& yyyy/mm/dd hh:mm:ss	Reads the date and time saved with the DA command.
CCn	&	Sets the type of calibration to be used:
		 User if n=0
		 Factory if n=1
		Default : Factory (n=1)
CO2D	&	Reset of user calibration.

Restoring the factory configuration:

Command	Reply	Description
DFLT	&	Restores the factory configuration.

6 MODBUS-RTU PROTOCOL

By default, the instrument has MODBUS address **1** and communication parameters 19200, 8E1. The address and the communication parameters can be changed by using the appropriate serial commands of the proprietary protocol or, alternatively, directly with MODBUS commands by changing the value of the Coils and Holding Registers described later.

The MODBUS-RTU protocol, if set as the operating protocol (default), is active after 10 seconds from the instrument power on.

In order to change the instrument configuration using the MODBUS-RTU protocol, the value 1 must be written first in the *Coil* with address 1.

Below is the list of registers.

Input Registers:

Address	Description	Format
0	PM1.0 in N° of particles/ml. Measurement averaged according to what is set with CPS command or MODBUS holding register 19.	16-bit Integer
1	PM2.5 in N° of particles/ml. Measurement averaged according to what is set with CPS command or MODBUS holding register 19.	16-bit Integer
2	PM10 in N° of particles/ml. Measurement averaged according to what is set with CPS command or MODBUS holding register 19.	16-bit Integer
3	PM1.0 in µg/m ³ (x10). Measurement averaged according to what is set with CPS command or MODBUS holding register 19.	16-bit Integer
4	PM2.5 in µg/m ³ (x10). Measurement averaged according to what is set with CPS command or MODBUS holding register 19.	16-bit Integer
5	PM10 in µg/m ³ (x10). Measurement averaged according to what is set with CPS command or MODBUS holding register 19.	16-bit Integer
6	PM1.0 in N° of particles/ml. Measurement averaged over 10 s and updated every sec- ond.	16-bit Integer
7	PM2.5 in N° of particles/ml. Measurement averaged over 10 s and updated every sec- ond.	16-bit Integer
8	PM10 in N° of particles/ml. Measurement averaged over 10 s and updated every sec- ond.	16-bit Integer
9	PM1.0 in µg/m ³ (x10). Measurement averaged over 10 s and updated every sec- ond.	16-bit Integer
10	PM2.5 in µg/m ³ (x10). Measurement averaged over 10 s and updated every sec- ond.	16-bit Integer

Address	Description	Format
11	PM10 in μg/m ³ (x10).	16-bit Integer
	<i>Measurement averaged over 10 s and updated every sec- ond.</i>	
12	PM1.0 in N° of particles/ml.	16-bit Integer
	Measurement averaged over 60 s and updated every 10 s.	
13	PM2.5 in N° of particles/ml.	16-bit Integer
	Measurement averaged over 60 s and updated every 10 s.	
14	PM10 in N° of particles/ml.	16-bit Integer
	Measurement averaged over 60 s and updated every 10 s.	
15	PM1.0 in μ g/m ³ (x10). Measurement averaged over 60 s and updated every 10 s.	16-bit Integer
16	PM2.5 in $\mu g/m^3$ (x10).	16-bit Integer
10	Measurement averaged over 60 s and updated every 10 s.	10 bit integer
17	PM10 in μg/m ³ (x10).	16-bit Integer
	Measurement averaged over 60 s and updated every 10 s.	5
18	PM1.0 in N° of particles/ml.	16-bit Integer
	Measurement averaged over 15 min and updated every mi- nute.	
19	PM2.5 in N° of particles/ml.	16-bit Integer
	Measurement averaged over 15 min and updated every mi- nute.	
20	PM10 in N° of particles/ml.	16-bit Integer
	Measurement averaged over 15 min and updated every mi- nute.	
21	PM1.0 in μg/m ³ (x10).	16-bit Integer
	Measurement averaged over 15 min and updated every mi- nute.	
22	PM2.5 in μg/m ³ (x10).	16-bit Integer
	Measurement averaged over 15 min and updated every mi- nute.	
23	PM10 in μg/m ³ (x10).	16-bit Integer
	Measurement averaged over 15 min and updated every mi- nute.	
26	PM measurement error: $0=no$, $1=yes$.	Intero 16 bit
28	CO ₂ in ppm.	Intero 16 bit
33	Atmospheric pressure in Pa (*)	Intero 32 bit
	Internal sensor for CO ₂ measurement compensation	
35	Atmospheric pressure in hPa (x10)	Intero 16 bit
	Internal sensor for CO ₂ measurement compensation	
37	Power supply voltage in Volt (x10).	16-bit Integer
38	Internal board temperature (x10).	16-bit Integer
40	Instrument firmware revision. The most significant byte in- dicates the major revision; the less significant byte indi- cates the minor revision.	16-bit Integer
41	Number of MODBUS communication error.	16-bit Integer

(*) The measure is a 32-bit integer value. Two consecutive registers (33 and 34) must be ac-

cessed to read the value. The register with lower address contains the most significant bits.

Со	il	S	:
CU		5	•

Address	Description	Format
0	Set 1 to restore the factory configuration. Bit zeroing is automatic.	Bit
1	Enable configuration change: 0=no (default), 1=yes. The changes to <i>Coils</i> and <i>Holding Registers</i> will be accept- ed only if this register is set to 1.	Bit
2	Sets waiting time after transmission with MODBUS-RTU pro- tocol: 0=immediate reception (default); 1=waiting 3.5 characters.	Bit
3	 Enable/disable the offset of the analog output 1: 0=offset disabled (020 mA or 010 V, default if the output is voltage); 1=offset enabled (420 mA or 210 V, default if the output is current). 	Bit
4	Sets the direct or inverse correspondence between analog output 1 and associated physical quantity: $0=4 \text{ mA/0 V} \Rightarrow \text{Min. quantity, } 20 \text{ mA/10 V} \Rightarrow \text{Max. quantity}$ (default); $1=20 \text{ mA/10 V} \Rightarrow \text{Min. quantity, } 4 \text{ mA/0 V} \Rightarrow \text{Max. quantity.}$	Bit
5	 Enable/disable the offset of the analog output 2: 0=offset disabled (020 mA or 010 V, default if the output is voltage); 1=offset enabled (420 mA or 210 V, default if the output is current). 	Bit
6	Sets the direct or inverse correspondence between analog output 2 and associated physical quantity: $0=4 \text{ mA/0 V} \Rightarrow \text{Min. quantity, } 20 \text{ mA/10 V} \Rightarrow \text{Max. quantity}$ (default); $1=20 \text{ mA/10 V} \Rightarrow \text{Min. quantity, } 4 \text{ mA/0 V} \Rightarrow \text{Max. quantity.}$	Bit

Holding Registers:

Address	Description	Format
0	RS485 Baud Rate: 0=1200; 1=2400; 2=4800; 3=9600; 4=19200 (default); 5=38400; 6=57600; 7=115200.	16-bit Integer
1	RS485 parity and stop bits: 0=8N1; 1=8N2; 2=8E1 (default); 3=8E2; 4=801; 5=802. [N=no parity, E=even parity, O=odd parity]	16-bit Integer
2	Instrument address for the MODBUS-RTU protocol (1247, default=1).	16-bit Integer
3	Association of a physical quantity to the analog output 1: 0=PM1.0; 1=PM2.5 (default); 2=PM10; 12=CO ₂ (only PMBsense-A). The PM measurement is averaged according to what is set with CPS command or MODPLUS holding register 10	16-bit Integer
6	Setting of the minimum value of the measuring range of the physical quantity associated to the analog output 1. ^(*)	32-bit Integer
	If the output is associated to PM, the value is expressed as a number of tenths (e.g. $5 = 0.5 \ \mu g/m^3$). If the output is associated to CO ₂ , the value is expressed as a number of units (e.g. 200 = 200 ppm). The default value is 0.	
8	Setting of the maximum value of the measuring range of the physical quantity associated to the analog output 1. $(*)$	32-bit Integer
	If the output is associated to PM, the value is expressed as a number of tenths (e.g. $50 = 5.0 \ \mu\text{g/m}^3$). If the output is associated to CO ₂ , the value is expressed as a number of units (e.g. $800 = 800 \ \text{ppm}$). The default value is $10000 \ (=1000.0 \ \mu\text{g/m}^3 \ \text{of PM})$.	
10	Association of a physical quantity to the analog output 2: 0=PM1.0; 1=PM2.5; 2=PM10 (default); 12=CO ₂ (only PMBsense-A). The PM measurement is averaged according to what is set	16-bit Integer
	with CPS command or MODBUS holding register 19.	

Address	Description	Format
11	Setting of the minimum value of the measuring range of the physical quantity associated to the analog output 2. $^{(*)}$	32-bit Integer
	If the output is associated to PM, the value is expressed as a number of tenths (e.g. $5 = 0.5 \ \mu g/m^3$). If the output is associated to CO ₂ , the value is expressed as a number of units (e.g. 200 = 200 ppm). The default value is 0.	
13	Setting of the maximum value of the measuring range of the physical quantity associated to the analog output 2. $^{(*)}$	32-bit Integer
	If the output is associated to PM, the value is expressed as a number of tenths (e.g. $50 = 5.0 \ \mu\text{g/m^3}$). If the output is associated to CO ₂ , the value is expressed as a number of units (e.g. $800 = 800 \ \text{ppm}$). The default value is $10000 \ (=1000.0 \ \mu\text{g/m^3} \ \text{of PM})$.	
15	Setting of the PM measurement mode: 0=continuous; 1=at cyclic intervals (default).	16-bit Integer
16	Setting of the cycle interval, in seconds, for the PM meas- urement mode at cyclic intervals. The default value is 300 (=5 min).	16-bit Integer Unsigned
18	Setting of the sensor ON time, in seconds, for the PM measurement mode at cyclic intervals. It must be greater than 70 s (warm-up time). The default value is 71.	16-bit Unsigned Integer
19	 Setting of the type of PM measurement averaging for the analog outputs and the measurements sent by the transmitter in reply to P1, P5, S1 and S5 commands (proprietary protocol) or when reading MODBUS Input Registers 05: 0=average over a 10 seconds interval, updated every second; 1=average over a 60 seconds interval, updated every 10 seconds (default); 2=average over a 15 minutes interval, updated every minute 	16-bit Integer
20	Setting of the type of CO ₂ calibration to be used: 0=user; 1=factory (default).	16-bit Integer

For 32-bit values, two consecutive registers must be accessed (e.g. 6 and 7 for the setting of the minimum value of the measuring range of the physical quantity associated to the analog output 1). The register with lower address contains the most significant bits.

7 SAFETY INSTRUCTIONS

General safety instructions

The instrument has been manufactured and tested in accordance with the safety standard EN61010-1:2010 "Safety requirements for electrical equipment for measurement, control and laboratory use" and has left the factory in perfect safety technical conditions.

The instrument proper operation and operating safety can be ensured only if all standard safety measures as well as the specific measures described in this manual are followed.

The instrument proper operation and operating safety can be ensured only in the climatic conditions specified in this manual.

Do not use the instruments in places where there are:

- Corrosive or flammable gases.
- Direct vibrations or shocks to the instrument.
- High-intensity electromagnetic fields, static electricity.

User obligations

The instrument operator shall follow the directives and regulations below that refer to the treatment of dangerous materials:

- EEC directives on workplace safety.
- National law regulations on workplace safety.
- Accident prevention regulations.

8 ACCESSORIES ORDERING CODES

- **CPM12-8PM.x** Cable with 8-pole M12 connector on one end, open wires on the other end. Length 2 m (CPM12-8PM.2), 5 m (CPM12-8PM.5) or 10 m (CPM12-8PM.10) standard, other lengths on request.
- **RS51K** Kit for connecting the transmitter RS485 output to a PC. It includes the SWD10 power supply and the RS485/USB adapter with:
 - screw terminals for the connection to the CPM12-8PM.x cable (not included);
 - USB connector for the connection to the PC;
 - jack connector for connecting the SWD10 power supply.

Notes



DICHIARAZIONE DI CONFORMITÀ UE EU DECLARATION OF CONFORMITY Delta Ohm S.r.L. a socio unico – Via Marconi 5 – 35030 Caselle di Selvazzano – Padova – ITALY

Documento Nr. / Mese.Anno: Document-No. / Month.Year :

5161 / 10.2020

Si dichiara con la presente, in qualità di produttore e sotto la propria responsabilità esclusiva, che i seguenti prodotti sono conformi ai requisiti di protezione definiti nelle direttive del Consiglio Europeo: We declare as manufacturer herewith under our sole responsibility that the following products are in compliance with the protection requirements defined in the European Council directives:

Codice prodotto: Product identifier :

PMsense-M / PMBsense-M PMsense-A / PMBsense-A

Descrizione prodotto: Product description :

Trasmettitori di Particolato (PM) e CO₂ Particulate Matter (PM) and CO₂ transmitters

I prodotti sono conformi alle seguenti Direttive Europee: The products conform to following European Directives:

Direttive / Directives		
2014/30/EU	Direttiva EMC / EMC Directive	
2014/35/EU	Direttiva bassa tensione / Low Voltage Directive	
2011/65/EU - 2015/863/EU	RoHS / RoHS	

Norme armonizzate applicate o riferimento a specifiche tecniche: Applied harmonized standards or mentioned technical specifications:

Norme armonizzate / Harmonized standards		
EN 61010-1:2010	Requisiti di sicurezza elettrica / Electrical safety requirements	
EN 61326-1:2013	Requisiti EMC / EMC requirements	
EN 50581:2012	RoHS / RoHS	

Il produttore è responsabile per la dichiarazione rilasciata da: The manufacturer is responsible for the declaration released by:

Alessandro Perego

Amministratore delegato Chief Executive Officer

Caselle di Selvazzano, 30/10/2020

Questa dichiarazione certifica l'accordo con la legislazione armonizzata menzionata, ner costituisce tuttavia garanzia delle caratteristiche.

This declaration certifies the agreement with the harmonization legislation mentioned, contained however no warranty of characteristics. **GHM GROUP – Delta OHM** | Delta Ohm S.r.l. a socio unico Via Marconi 5 | 35030 Caselle di Selvazzano | Padova | ITALY Phone +39 049 8977150 | Fax +39 049 635596 www.deltaohm.com | sales@deltaohm.com



WARRANTY

Delta OHM is required to respond to the "factory warranty" only in those cases provided by Legislative Decree 6 September 2005 - n. 206. Each instrument is sold after rigorous inspections; if any manufacturing defect is found, it is necessary to contact the distributor where the instrument was purchased from. During the warranty period (24 months from the date of invoice) any manufacturing defects found will be repaired free of charge. Misuse, wear, neglect, lack or inefficient maintenance as well as theft and damage during transport are excluded. Warranty does not apply if changes, tampering or unauthorized repairs are made on the product. Solutions, probes, electrodes and microphones are not guaranteed as the improper use, even for a few minutes, may cause irreparable damages.

Delta OHM repairs the products that show defects of construction in accordance with the terms and conditions of warranty included in the manual of the product. For any dispute, the competent court is the Court of Padua. The Italian law and the "Convention on Contracts for the International Sales of Goods" apply.

TECHNICAL INFORMATION

The quality level of our instruments is the result of the continuous product development. This may lead to differences between the information reported in the manual and the instrument you have purchased. In case of discrepancies and/or inconsistencies, please write to sales@deltaohm.com. Delta OHM reserves the right to change technical specifications and dimensions to fit the product requirements without prior notice.

DISPOSAL INFORMATION



Electrical and electronic equipment marked with specific symbol in compliance with 2012/19/EU Directive must be disposed of separately from household waste. European users can hand them over to the dealer or to the manufacturer when purchasing a new electrical and electronic equipment, or to a WEEE collection point designated by local authorities. Illegal disposal is punished by law.

Disposing of electrical and electronic equipment separately from normal waste helps to preserve natural resources and allows materials to be recycled in an environmentally friendly way without risks to human health.



V1.3 09/2021